

MAPLE THIN CLIENT UZAKTAN YÖNETİM PROGRAMI



Kurulum ve Kullanım Kilavuzu

PC & Laptop veya Sunucu üzerine yüklenebilir.

MAPLE TEKNOLOJİ A.Ş. Tel : 0216. 456 58 96 Fax : 0216. 548 13 75 Atatürk Mah.Şeref Sk.No:18/1 D:2 34750 Ataşehir / İstanbul e-mail: <u>maple@maple.com.tr</u> <u>www.maple.com.tr</u>

KURULUM

1 – Maple SNMP CD'sini bilgisayarın sürücüsüne yerleştirin.



CD – Rom sürücüsü

2. Çift tıklayarak çalıştırınız; SETUP dosyasının üzerinde iki kere tıklayınız.





4. Next tıklayınız.

🖉 WBT Some Admini	strator Installation
ag wer simp Aumin	Registration Information
	Please enter the name and company of the registered owner of WBT Snmp Administrator into the fields below.
	Registered user's full name:
*** ***	Registered user's company name:
	Registered user's serial number:
	< <u>B</u> ack <u>N</u> ext > <u>C</u> ancel

Seri numarası olarak 1 veya herhangi bir sayı girin. Daha sonra Next tıklayınız.



Next tıklayınız.

6



Next tıklayınız.



Next tıklayınız.

8.



Next tıklayınız.

9. Kurulum başlayacaktır.

Installing 🛛 🔀
Copying file: C:\Program Files\SnmpAdm\SnmpAdm.exe
63%
Cancel

10.



Kurulum bittikten sonra Finish'i tıklayınız.

11.

Bilgisayarınızda programların içerisinde yüklenmiş olan SNMP programının kısa yolunu bilgisayarınızın masaüstüne kopyalayın.



12.



13. User Name (kullanıcı adı) Administrator olarak gelir. Password boş dilediğiniz zaman Password verebilirsiniz.



See 23							
1) Ad	dress Firmv	vare Version	MAC Address	Status	Group Name	Client Name	Flash
5	192.168.0.5 WBT	-E5518.1	0050AC75017B			T75017B	3
						1	
			_				
10	hertis) Selected						
Hum builden be	contration and a second	Dereste Dete		_	Di		
ota Satting Trap Massaga	Margana History	Schadular	n Thin@fant Database	Demo	LASCOVE	ny Logs (/ Svetam Conferenti	
the centry in the new stage	incode includy	Concours	ranoien ponease	- Out	ac mages	of press considerate	UTD I
**	Ident		Value	_			-
m	Vnc Viewer Part		5900	5900			
	User1		Users Administ	Users Administrator			
Administrator	Description		Administrator	Administrator			
Administrator	Name		administrator	administrator			
Administrator	Password						
Administrator.Permits	Database		1				
Administrator Permits	Discovery Logs		1				
Administrator Permits	Patch manager		0				
Administrator Permits	Reboot		1				
	1.1.1.1.1						
se View as Text (Read only)							
1 0 8 / " Manhaire	tech Farmers - Chi same		MP Education and		TR	0003403	12-48
	and the state	4 3				23 9 9 9 9 9 D 3	

KULLANIM

14. SNMP programı açıldığında Network üzerinde olan Maple marka thin clientlar listelenmiş olur.

Önemli Not : SNMP programıyla listelenen thin clientlar mutlaka <u>MAPLE</u> <u>Thin Client</u> olmak zorunda başka marka thin clientlar gözükmez.

SNMP Administrator 2.0.	194.7			_		<u> </u>
<u>F</u> ile ⊻iew <u>H</u> elp						
Groups Subnets	Clients					
			M			
All (1)	Address	Fin	mware Version	MAC Address	Status	Group Name
	192. Te	18.U.9 XP	E-5mt5612k-51	0050AC75279	r	•
Remote Images	System Configu	Irations	Users /	And Permits	Remot	te Patch
Remote Setting	Trap Message	Message H	istory	Schedules	ThinClient	Database
- 🎯 My Remote Setting		Name	(·	Гуре	Data	
		•				

Ağ üzerindeki bağlı olan Thin Clientlar listesi IP adresleriyle birlikte görülür.

15. İşlem yapmak istediğiniz thin client kullanıcısının üzerinde mouse sağ tıklayınız.

SNMP Administrator 2.0.194.3	7	_	
Groups Subnets		Clients	
			😤 🖃 🔮 🙆 🛤
Address Mask	s	Address	s Firmware Version
192.168.0.0 (1) 255.255.255.0		192	Ti New Ti Delete Select All Ctrl+A
			Messages
<u>₹</u>	Þ	1 Clien	Image: Second second
Remote Images	Syst ap Messa	em Conf ige	O Shutdown ers And Reboot S
			Reset To Default

16. Messages : Kullanıcıya ileti mesajı gönderebilirsiniz.

SNMP Administrator 2.0.194.7		_ D X
<u>F</u> ile ⊻iew <u>H</u> elp		
Groups Subnets	Clients	
Address Mask S	Address Firmware Version MAC Address Status	Group Na
192.168.0.0 (1) 255.255.255.0	192.168.0.9 XPE-5mt5612k-S1 0050AC75279F	
	Send Messages	×
	Makinayi Kapata bilirmisn	
Demote Imegae	an Configuration	
Remote System System System System System System System Strength System	age M	
mg My Remote Setting	Allow Reply	

17. Remote Display : Bulunduğunuz yerden kullanıcının bilgisayarına uzaktan bağlanabilirsiniz.

SNMP Administrator 2.0.194.7				
<u>F</u> ile ⊻iew <u>H</u> elp				
Groups Subnets	Clients			
▰▰▰▻▻♥♥		• 🖳 💣 🙆 🛤		
Address Mask S	Address	Firmware Version	MAC Address	Status Group Name
192.168.0.0 (1) 255.255.255.0	192.168.0.9	XPE-5mt5612k-S1	. 0050AC75279F	Ē
		∑ <u>N</u> ew <u>D</u> elete Select <u>A</u> ll Ctrl+A		
		🖃 Messages 🗐 <u>R</u> emote Display		
<u>د ا</u>	I Client(s) Sel	🕵 <u>U</u> pgrade 🎯 Registry <u>E</u> ditor		•
Remote Images Syst	em Configuratio	Shutdown	Permits	Remote Patch
Remote Setting Irap Messa	ige iv	Reboot	chedules	ThinClient Database
		Reset To Default		
🛛 💣 My Remote Setting		Name (Ty	pe	Data
		त		

18. Bağlanılan kullanıcının thin client masaüstü.

MP Admi	V ² XPEMB75279F	
: View		
ients	My Documents	
il 💷 🧖 Idress	I	
192.16	My Computer	
	S	
	Places	
Client(s	Diternet	
Configu	Explorer	
	Remote	
	Desktop Connection	
	TouchKit	
	🎒 Start 🛛 🍏 🎯 🗍	 2 🕼 14:23

19. Upgrade: Tek merkezden upgrade yapabilirsiniz.

SNMP Administrator 2.0.194.7								x
EileiewElp								
Groups Subnets	Clients							
		=	💣 🖸 🚧					
Address Mask S	Address		Firmware Versior	n [MAC Address	Status	Group	Name
192.168.0.0 (1) 255.255.255.0	192.168.0	.9	New Sectors	24	0050AC75279F			
		+ + + + + + + + + + + + + + + + + + +	<u>N</u> elete					
			Select <u>A</u> ll Ctrl+	A				
		-	Messages					
			<u>R</u> emote Display					
	•	- 😤	<u>U</u> pgrade					Þ
	1 Client(s) S	ele 💣	Registry <u>E</u> ditor					1
Remote Images Sys	tem Configurati	on 💿	<u>S</u> hutdown		Permits	Remote	Patch	
Remote Setting Trap Mess	age	Me	Reboot		hedules	ThinClient D	Databasi	2
			Reset To Defaul	lt				
ở My Remote Setting		Name	,	Туре		Data		

20. Registry : Sistem ayarlarını kontrol edebilirsiniz.

SNMP Administrato	r 2.0.194.7				
<u>F</u> ile ⊻iew <u>H</u> elp					
Groups Subnets		Clients			
ず≦╬⊡₽₽		₽ i ±i ¢	8 📼 🖳 💰	10	
Address Mas	k [:	S Address	[Fii	rmware Versio	n
192.168.0.0 (1) 255.	255.255.0	192.16	⊅ ≦New		<u> 31</u>
			± <u>D</u> elete		
			Select A	II Ctrl+A	
			🖃 Messagi	es	
			🖳 <u>R</u> emote	Display	
			😤 Upgrade	3	
T		1 Client(s	💣 Registry	/ <u>E</u> ditor	
Remote Images	Sγ	stem Configu	💿 <u>S</u> hutdow	vn	An
Remote Setting Trap Message			Reboot		
<mark>Ľ≓</mark> ≓≣			Reset T	o Default	
A					~

SNMP Administrator 2.0.194	1.7				
<u>F</u> ile ⊻iew <u>H</u> elp					
Groups Subnets	Clients				
≓≝ <u>®</u> ⊡>®®	SNMP Administrator Registry Editor				x
Address Mask	Eile				
192.168.0.0 (1) 255.255.255	 ■ 192 168.0.9 ■ HKEY_CLASSES_ROOT ■ HKEY_CURRENT_USER ■ HKEY_LOCAL_MACHINE 	Name) Туре] Data	
Remote Images Remote Setting					
	192.168.0.9	•			•

SNMP Administrator 2.0.194.7		
<u>F</u> ile <u>∨</u> iew <u>H</u> elp		
Groups Subnets	Clients	
	#####\$ * == !!! # 10 #\$	
Address Mask S	Address Firmware Version	MAC Address Status Group Nam
192.100.0.0 (1) 205.205.205.0		. 0060AC75279F
Remote Images Syste Remote Setting Trap Messa	m C 🗿 Shutdown Users An 3e Reboot	nd Permits Remote Patch Schedules ThinClient Database
	Reset To Default	
🦷 🎰 My Remote Setting	Name Ty	rpe Data

21. Shutdown: Kullanıcı thin clientı kapatabilirsiniz.

22. A Kapalı thin clientları Wakep On Lan 'ı tıklayarak açmak istediğiniz thin client'in IP adresini seçerek açabiliriz.

SNMP Administrator 2.0.194.7										
<u> </u>	' <u>H</u> elp									
Groups Sub	Groups Subnets Clients									
* 1=1 %	⊐₽₿₪		71 II (1		4					
Address	Mask	S	Address	Firmware	Version	MAC Address	(St	atus	Group I	Name
192.168.0.0 (New Delete Discover Discover from ■ Messages Wakeup On I 	Ctrl+F n Databasi _an	2.168.0 e	0.9 XPE-5mt5	5612k-S1	0050AC75279	F			
₹	🕵 <u>U</u> pgrade		ent(s)							
Remot	e Images	Syste	m Configurat	ons Users And Permits R				Remote Patch		
Remote	Setting T	irap Messa	ge	Message History	S	chedules	Thir	nClient D	atabase	
<mark>₿</mark> ₹i±i										
🚽 🔐 🎯 My Re	emote Setting			Name	Тур	e	Data			
				٩						P



23. Thin Client XPe image alma ve imajdan geri yükleme.

	histrator 2.0.194.7									
<u> </u>	<u>H</u> elp									
Groups Subnet:	s	Clients								
All (1)		Address Fir	Address Firmware Version MAC Address Status Group Name							
		2011 102.168.0.9 XF	PE-5mt5612k-S1	. 0050AC75279F						
		I Client(s) Selected								
Remote Set	tting Trap Mess	sage Message H	History S	Schedules	ThinClient Database					
Remote In	nages Sys	tem Configurations	Users An	nd Permits	Remote Patch					
Images Server	Logs									
Name	Description Fin	mware Version 🛛 🗌 Re	mote Path Tim	neout (Image File						
₹										

Remote images bölümünü tıklayınız.

24. Image Alma Yöntemi

Images almak istediğimiz thin client üzerine gelip mouse ile tutup remote images kısmına bırakılır . Açılan pencerede nereye imaj almak istediğimizi sorar. Yerini belirleyip image için bir isim verilip OK tuşuna basılır. Image'ın alındığı thin client kapanır ve açıldığında yukarı kısımda saymaya başlar. Ayrıca SNMP programının içerisinde % olarak takip etme olanağınada sahipsiniz. Sayma işlemi bittikten sonra thin client images'ı alınmış olur.

SNMP Administrator 2.0.194.7		×
<u> </u>		
Groups Subnets	Clients	
All (1)	Address Firmware Version MAC Address Status Group	Name
	192.168.0.9 XPE-5mt5612k-S1 0050AC75279F	
	New Image	
	Name: XPEMB75279E 192.168.0.9	
	Type: XPe	
	Eirmware Version XPE-5mt5612k-S1.0.1.157	
	I1 Client(s) Sel Description /dev/hda2	
Remote Setting Trap Messa	sage M Image File:	
Remote Images Syst	tem Configuratio	
Images Server Logs	Remote Image Path	
Name Description Firm	mware Version	
	V XPe Reseal	
I		Þ

Image Geri Yükleme

Image'dan geri yükleme bu sefer alt kısımdaki Remote Images açılır. Almış olduğunuz imaj dosyasını mouse ile tutup sürükleyerek yukarıdaki hedef thin client üzerine bırakılır. Thin client kapanır. Açıldıktan sonra saymaya başlar bittikten sonra yeniden başlayarak XPe normal açılır.

SNMP Administrator 2.0, 195, 12					_			3 × 1
Fig. vice inclu								
Corps Silvers	Ci-u -							
*****	📬 👘 🛃 📼 👳	1 10 11						_
A1 ())	Autometers	From - Versio		V=0 = nh-se	S stu-	Composition	Ci-n varia] =1
	∰162 3£ 1.#	WEI-E \$216-1		009040760.75			1776) 75	
	7							
	/							
	/							
	<u> </u>							
	Citor (+) Selecter	ıl						
. sopewint Mormile	L Marriero a		Remaie – atch			Lince:	т; <u>10:6</u>	
Remote Sector: Factorescare	nicisca: el lo	10 •2 C.e.	.ue: 1	The Bene Li atabase	E:Em:	tie magas 📙	2-2-yale Calma u a	- III III III III III III III III III I
varie Ze-orpino Fin	awara Maistor	Terro - Pallo		<u>у-Fiн</u>			Fla a	
A PERCIPAL ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDRESS ADDR	неней байтан Li umpD/Tulla S1 U	(dowindo	L D)	nadouce&ination nadouce&ination	na zemen na zemenna	1-2 1 1-5 -01- ta:m:		
STEVESTOR describe of	5-6m-57126-S D	dest de	36 D.>	ad-VotShar Terr	5 24.H ×	· 1,		
SALTTLES Addende X-L	u umetik fulle Siriu	(dewinder Mittanal	μ D): ≫ α∵	nadouceUs name in	1012-0011-a-	a smr		
SA FERCIAL AREA IN A P	Decidiardo (Cillado) — 1	-0-s" 0s	a 107	COLUMN AND AND AND AND AND AND AND AND AND AN				
74 start 0 6 /6 * 10 mm	- a resolution 🛛 🗖	THERE IS DOTHER.		- an	387 8.1 2	autor ==	金属 化合相 伊	🚳 1- 12
				1.46				

25. Ağ üzerinde mevcut başka sunucu varsa IP adreslerini yazarak bulabilirsiniz.

SNMP Adm	ninistrator 2.0.1	94.7								×	
Eile ⊻iew <u>H</u> elp											
Groups Subn	ets		Clients								
*1 == % =											
Address	Mask	s (Address	Fin	mware Versio	on 🛛 MAC Addre	ess	Status	Group	Name	
192.168.0.0 <mark>(</mark> 1	ಘ ∶ <u>N</u> ew		2.168.0).9 XP	E-5mt5612k-	S1 0050AC752	279F				
	<u>±§D</u> elete										
	P Disco⊻er	Ctrl+F	5								
	Discover f	rom Database	e								
	🖃 <u>M</u> essages	i									
	🔊 <u>W</u> akeup C)n Lan									
T	😤 <u>U</u> pgrade		nt(s)								
Remote	e Images	Syster	m Configurat	ions	Users And Permits			Remote Patch			
Remote S	Setting	Trap Messag	le 🛛	Message H	istory	Schedules		ThinClient Databas			
<mark>ĭ;</mark> ;											
🦳 🎯 My Rem	mote Setting			Name		Туре	Da	ata			
				<u>ا</u>						×	

SNMP Administrator 2.0.194.7		- - X
<u>F</u> ile ⊻iew <u>H</u> elp		
Groups Subnets	Clients	
Address Mask S	Address Eirmware Version MAC Address Status	Group Name
192.168.0.0 (1) 255.255.255.0	192.168.0.9 New Subnet	
	Subnet Address: 192.168.0.25 (Örnek)	
	Sample: 192.168.(*).0	
	Erom: 1 🚔 To: 255 🚔 Step: 1 🚔	
	1 Client(s)	
Remote Images Syst	tem Configurations	tch
Remote Setting Trap Mess	age Messa	abase
	Subnet Mask: 255,255,255,0	
🦾 🎯 My Remote Setting	Nam Start Address:	
	Address Count:	
	✓ Ok X Cancel	
	<u> </u>	

26. Sunuculardaki thin client 'ları aratabilirsiniz.

SNMP Adm	inistrator 2.0.1	94.7										
<u> </u>	<u>H</u> elp											
Groups Subne	ets		Clients	Dients								
; ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;			$\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} $									
Address	Address Mask S			s [F	irmware Versio	n 🛛 MAC Addre	ss	Status	∫Group Name			
192.168.0.0 (1)	255 255 26	55.0	192.1	168.0.9 X	PE-5mt5612k-8	S1 0050AC752	79F					
	⊋ ` <u>} N</u> ew		- 1									
	± <u>n D</u> elete		- 1									
	₽ Discover	Ctrl+	F5									
	Discover 1	from Databa	ise									
	🖃 Messages	3										
	Wakeup (On Lan	- F									
				t(e)								
	• <u>v</u> pgrade	_		.(5)								
Remote	Images	Syste	em Confi	gurations	Users	And Permits		Remote	Patch			
Remote S	etting	Irap Messa	ige	Message	History	Schedules	_	ThinClient L	Jatabase			
🦳 🎯 My Rem	note Setting			Name		Туре	Da	ata				
<u> </u>												